

| Typ | Výrobce | U_f | I_f | U_a | I_a | $-U_{g1}$ | S | R_i |
|------------|------------|-------|-------|--------------------|-------------------|-----------|------|------------|
| 1 | 2 | V | A | V | mA | V | mA/V | k Ω |
| 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 |
| OQQ50/1000 | Tungsram | 7,5 | 4 | 1500 | 125 | 150 | — | — |
| | | | | 1250 | 100 | 150 | — | — |
| | | | | 1500 | 190 | 22,5 | — | — |
| OQQ50/1500 | Tungsram | 7,5 | 4 | 1500 | 125 | — | 2 | 23,5 |
| OT100 | Tungsram | 10 | 3,25 | 1750 ¹⁾ | — | — | — | — |
| | | | | 1250 | 200 | — | — | — |
| | | | | 1750 | 250 | — | — | — |
| | | | | 1250 | 85 | 65 | — | — |
| | | | | 1000 | 160 | 195 | — | — |
| OT400 | Tungsram | 10 | 10,6 | 4000 ¹⁾ | — | — | — | — |
| | | | | 4000 | 100 | 100 | — | — |
| | | | | 4000 | 150 | 120 | — | — |
| | | | | 3000 | 415 | 300 | — | — |
| | | | | 4000 | 500 | 500 | — | — |
| P100/1000 | Tungsram | 6 | 2,5 | 1250 | 110 | 210 | — | — |
| P100/1250 | Tungsram | 10 | 3,25 | 1250 ¹⁾ | 150 ²⁾ | — | 4 | 3 |
| | | | | 1250 | 150 | 153 | — | — |
| PR4B | Gecovalve | 11 | 2,5 | 2000 ¹⁾ | — | — | 6 | 4 |
| R253 | Telefunken | 16,5 | 16,5 | 12000 | — | — | 8 | 6,25 |
| RD12Tf | Telefunken | 12,6 | 0,6 | 400 | 90 | — | 16 | 3,4 |
| RS15 | Telefunken | 16,6 | 17,5 | 4000 | — | — | 3,5 | 1,45 |
| RS18 | Telefunken | 16 | 8,8 | 3000 | — | — | 2,5 | 2,2 |
| RS19 | Telefunken | 14 | 4,8 | 3000 | — | — | 15 | 4,75 |
| RS31 | Telefunken | 10 | 4,8 | 1600 | — | — | 1,3 | 2,55 |
| RS47 | Telefunken | 16 | 8 | 10000 | — | — | 2,5 | 50 |
| RS55 | Telefunken | 10 | 3 | 700 | 35 | 25 | 1,1 | 18 |
| RS69 | Telefunken | 10,3 | 2,75 | 1000 | — | — | 5 | 46 |
| RS207 | Telefunken | 16,5 | 18 | 5000 | 500 | — | 4 | 12,5 |
| RS207A | Telefunken | 16,5 | 16 | 10000 | — | — | 4,5 | 11 |
| RS212 | Telefunken | 12,5 | 6 | 4000 | 120 | — | 1,6 | 12,5 |
| RS214 | Telefunken | 22 | 13 | 2000 | 370 | — | 4 | 8 |
| RS215 | Telefunken | 22 | 23 | 4000 | 750 | — | 5 | 10 |
| RS217 | Telefunken | 17,5 | 56 | 11000 | 1650 | 850 | 12 | 1 |
| RS233 | Telefunken | 10 | 4,3 | 1600 | — | — | 2 | 7 |
| RS234 | Telefunken | 10 | 3,3 | 1000 | — | — | 4 | 3 |
| RS235 | Telefunken | 10 | 3,5 | 1000 | 200 | — | 4 | 3 |
| RS237 | Telefunken | 10 | 3,25 | 1250 ¹⁾ | 150 ²⁾ | 153 | 4 | 3 |
| | | | | 1250 | 150 | 153 | — | — |
| | | | | — | — | — | — | — |
| RS243 | Telefunken | 10 | 3,25 | 1250 | 150 | 225 | — | — |
| | | | | 1000 | 150 | 225 | — | — |
| | | | | 1250 | 320 | 100 | — | — |
| RS249 | Telefunken | 12,6 | 40 | 600 | — | 60 | 3,5 | 5,7 |
| RS250 | Telefunken | 17,5 | 120 | 11000 | 2700 | 70 | 12 | 6,4 |

| R_a | P_0 | P_v | μ | C_{ag} | Poznámky | Typ | Pa- tice |
|--------------------|-------------------|-------|-------|----------|---|------------|-------------|
| k Ω | W | W | | | | | |
| 10 | 11 | 12 | 13 | 14 | 15 | 16 | 17 |
| — | 50 | 140 | 47 | 2,8 | zes C; A1; $P_b=9,5$ W; $I_{g1}=35$ mA; $R_k=940$ | OQQ50/1000 | 900 |
| — | 35 | 95 | — | — | zes C; A3; $P_b=7,5$ W; $I_{g1}=30$ mA; mod/a | | |
| 18,3 ¹⁾ | — | 185 | — | — | zesv nf; $P_b=4,8$ W; zes B; ¹⁾ R_{aa} | | |
| — | 50 | 140 | 47 | — | zes C; zes vf; osc; = 1,1 m | OQQ50/1500 | |
| — | — | — | 20 | 5 | $C_{gk}=6,4$ pF; $C_{ak}=1$ pF; $f=50$ Mc/s; ¹⁾ max | OT100 | |
| 8 ¹⁾ | — | 250 | — | — | ¹⁾ R_{aa} ; mod; $P_b=4$ W; zesv nf; zes B | | |
| — | — | 330 | — | — | zes C; A1; osc; $R_{g1}=2000$ Ω ; $I_{g1}=35$ mA | | |
| — | 75 | 40 | — | — | zes B; A3; $I_{g1}=2$ mA; $P_b=5,5$ W | | |
| — | 115 | 50 | — | — | zes C; A3; mod/a; $I_{g1}=28$ mA; $P_b=9$ W; $R_{g1}=7000$ Ω ; $U_{a\max}=1750$ V | | |
| — | 400 | — | 35 | 6,3 | $C_{gk}=12,3$ pF; $C_{ak}=8,5$ pF; ¹⁾ max | OT400 | |
| 12 ¹⁾ | 400 | 2400 | — | — | mod; ¹⁾ R_{aa} ; $P_b=29$ W; zesv nf; zes B | | |
| — | 400 | 225 | — | — | zes B; A3; $I_{g1}=2$ mA; $P_b=14$ W | | |
| — | 270 | 1000 | — | — | zes C; A3; mod/a; $I_{g1}=2$ mA; $P_b=37$ W; $R_{g1}=3600$ Ω | | |
| — | 400 | 1440 | — | — | zes C; A1; osc; $R_{g1}=2650$; $R_k=380$ Ω ; $I_{g1}=75$ mA | | |
| 10 ¹⁾ | — | 100 | — | 8,8 | zesv nf; PP; zes AB; ¹⁾ R_{aa} ; $U_{g\text{ef}}=300$ V; $I_{a\text{sig max}}=120$ V | P100/1000 | |
| — | 85 ²⁾ | — | 12 | 13 | $f=6$ Mc/s; ¹⁾ ²⁾ ³⁾ max | P100/1250 | |
| — | — | 140 | — | — | zes C; A1; osc; $I_{g1}=11,5$ mA | | |
| — | 250 ²⁾ | — | 25 | — | ¹⁾ ²⁾ max | PR4B | |
| — | 800 | 2500 | 50 | 6 | $C_{gk}=13$ pF; $C_{ak}=1,5$ pF | R253 | |
| — | — | — | — | — | $f_{\max}=700$ Mc/s; $I_{g1}=20$ mA | RD12Tf | |
| — | 700 | 1500 | 50 | — | | RS15 | |
| — | 350 | 450 | 55 | 8 | $C_{gk}=15$ pF; $C_{ak}=1,5$ pF | RS18 | |
| — | 150 | 175 | 71 | 6 | $C_{gk}=9$ pF; $C_{ak}=0,6$ pF | RS19 | |
| — | 75 | 65 | 33 | 5 | $C_{gk}=8$ pF; $C_{ak}=1$ pF | RS31 | |
| — | 550 | 100 | 125 | 6,5 | $C_{gk}=14$ pF; $C_{ak}=1$ pF | RS47 | |
| — | 15 | 12 | 20 | 5,5 | $C_{gk}=7$ pF; $C_{ak}=0,2$ pF | RS55 | |
| — | 20 | 25 | 33 | 8,5 | $C_{gk}=11$ pF; $C_{ak}=1,5$ pF | RS69 | |
| — | 800 | 1800 | 50 | — | $f_{\max}=75$ Mc/s | RS207 | |
| — | 1250 | 2500 | 50 | — | | RS207A | |
| — | 250 | 250 | 50 | — | $I_{g1}=10$ mA; $P_b=4,2$ W | RS212 | |
| — | 350 | 440 | 32 | — | $f_{\max}=15$ Mc/s | RS214 | |
| — | 1000 | 1800 | 50 | — | $f_{\max}=15$ Mc/s | RS215 | |
| — | 12000 | 12000 | 12,5 | — | A3; zes B; $f=3$ Mc/s; $I_{g1}=150$ mA; $P_b=190$ W | RS217 | |
| — | 75 | 40 | 14 | 4,5 | $C_{gk}=8$ pF; $C_{ak}=1$ pF | RS233 | |
| — | — | 120 | 12 | — | | RS234 | |
| — | — | 42,5 | 12 | — | $f_{\max}=15$ Mc/s | RS235 | |
| — | 85 ²⁾ | — | 12 | 13 | $f=6$ Mc/s; ¹⁾ ²⁾ ³⁾ max | RS237 | |
| — | — | 140 | — | — | A1; zes C; osc; $I_{g1}=11,5$ mA | | |
| — | 100 | 130 | — | 14,5 | A1; zes C; $I_{g1}=18$ mA; $P_b=17$ W; $I_{a\max}=175$ mA | RS243 | |
| — | — | 100 | — | — | A3; zes B; $I_{g1}=35$ mA; $P_b=14$ W | | |
| — | — | 260 | — | — | zesv nf; zes B; $P_b=8$ W | | |
| — | 13 | 12 | 20 | — | $f_{\max}=200$ Mc/s | RS249 | |
| — | 12000 | 20000 | 77 | — | A3; zes B; $f=3$ Mc/s; $I_{g1}=600$ mA; $P_b=450$ W | RS250 | |